

PROGRAMING THE SHARP XE-A101, XE-A102, XE-A106

READ THE EASY SET-UP GETTING STARTED INSTRUCTION SHEET FOR MORE DETAILS.

**INSERT ONE OF THE SUPPLIED MODE KEYS INTO THE
MODE SWITCH AND TURN IT TO THE REG POSITION
INSERT THE PLUG INTO AN AC OUTLET
A BUZZER WILL SOUND THREE TIMES
AND THE DISPLAY WILL SHOW "0.00" WITH "L"**

**IMPORTANT: THIS OPERATION MUST BE PERFORMED
BEFORE YOU INSTALL BATTERIES.**

NOW INSTALL BATTERIES AND PAPER AS PER INSTRUCTION SHEET.

- 1 TURN MODE SWITCH TO [Z/PMG] AND ENTER THE TIME IN 4 DIGITS ("hhmm" format) USING THE 24 HOUR SYSTEM.
PRESS THE [SBTL] KEY ONCE.
(IE: for 7:00 am = 0700, for 2:00 pm 1400.
- 2 NOW ENTER THE DATE USING 6 DIGITS. (month-day-year) IE: November 10, 2013 = 111013, April 2, 2014 = 040214
PRESS THE [SBTL] KEY TWICE, which ends this part of the programing.

3 SETTING UP THE PLU CODES

EXAMPLE OF NO PROFIT CODES

PRESS 1 THEN THE [PLU] KEY THEN INPUT 50 AND \PRESS THE [DEPT 1] KEY ... THEN 2 SHOULD APEAR ON THE SCREEN
INPUT 100 AND PRESS THE [DEPT1] KEY ... THEN 3 SHOULD APPEAR ON THE SCREEN
INPUT 150 AND PRESS THE [DEPT1] KEY ... THEN 4 SHOULD APPEAR ON THE SCREEN
INPUT 200 AND PRESS THE [DEPT1] KEY ... THEN 5 SHOULD APPEAR ON THE SCREEN
INPUT 250 AND PRESS THE [DEPT1] KEY ... THEN 6 SHOULD APPEAR ON THE SCREEN
INPUT 300 AND PRESS THE [DEPT1] KEY ... THEN 7 SHOULD APPEAR ON THE SCREEN
INPUT 400 AND PRESS THE [DEPT1] KEY ... THEN 8 SHOULD APPEAR ON THE SCREEN
INPUT 500 AND PRESS THE [DEPT1] KEY ... THEN 9 SHOULD APPEAR ON THE SCREEN
INPUT 600 AND PRESS THE [DEPT1] KEY ... THEN 10 SHOULD APPEAR ON THE SCREEN
INPUT 700 AND PRESS THE [DEPT1] KEY ... THEN 11 SHOULD APPEAR ON THE SCREEN
INPUT 800 AND PRESS THE [DEPT1] KEY ... THEN 12 SHOULD APPEAR ON THE SCREEN
INPUT 900 AND PRESS THE [DEPT1] KEY ... THEN 13 SHOULD APPEAR ON THE SCREEN
INPUT 1000 AND PRESS THE [DEPT1] KEY ... THEN 14 WILL APPEAR ON THE SCREEN
INPUT 1250 AND PRESS THE [DEPT1] KEY ... THEN 15 WILL APPEAR ON THE SCREEN
INPUT 1500 AND PRESS THE [DEPT1] KEY ... THEN 16 WILL APPEAR ON THE SCREEN
INPUT 25 AND PRESS THE [DEPT1] KEY ... THEN 17 WILL APPEAR ON THE SCREEN
NOW PRESS [SBTL] TO END PROGRAMING
THE CASH REGISTER WILL PRINT OUT A CONFIRMATION OF PRICES PER PLU



USING THE MACHINE

WHEN RINGING UP AN ITEM ENTER THE PRICE CODE AND PRESS THE PLU KEY (PLU = PRICE LOOK UP)

(IE: To Ring up a PC 03 item you would press the [3] key and the [PLU] key)

When you have finishing ringing up all of the items for one customer press the [SBTL] key to find out how much they owe. Now enter the amount of money given to your and press the

Blue [CA/AT/NS] key to print out a receipt and find out how much change to give to your customer.

At the end of the day turn the mode key to X and press the large Blue [CA/AT/NX] key to find out how much you have sold so far.